



## Specifications

Autonomy	<b>5 h / 100% - 8.5 h / 50%</b>
DC terminals thermal protection	<b>8,3 A</b>
Dimensions	<b>590 x 456 x 511 mm</b>
Engine	<b>4st combustion</b>
Engine displacement	<b>212 cc</b>
Fuel	<b>Petrol 95</b>
Max. Power	<b>3.5 kVA</b>
Maximum power - AC sockets	<b>3.5 kW</b>
No-load Speed	<b>3600 rpm</b>
Power factor (cos Ø)	<b>1</b>
Product weight	<b>45 kg</b>
Rated current - AC sockets	<b>15,2 A</b>
Rated power	<b>5.8 cv / 4.3 kW</b>
Rated power - AC sockets	<b>3.2 kW</b>
Rated voltage - DC terminals	<b>12 V</b>
Sound power level (LWA)	<b>95 dB</b>
Tank capacity	<b>8,3 L</b>

## INVERTER GENERATOR 3000

### VIGI3000

The VITO's Inverter Generator (VIGI3000) features a 4-stroke, 5.8 hp | 4.3 kW petrol combustion engine and has a 5-hour continuous running time. Its inverter technology makes the generator more efficient, keeping the electric current supplied stable and without oscillations. It is suitable for various types of uses, from home, garden, camping, caravans, among others. This equipment is silent and has electric start, 2 AC 230V sockets, a nominal power of 3.2 kW and a maximum power of 3.5 kW. Furthermore, it is equipped with oil level and current overload warning indicator lights. With a compact and portable design, the inverter generator has an aluminium handle and two wheels for safe transportation of the machine.

### Key features

- > Suitable for:
- > - Home;
- > - Garden;
- > - Camping;
- > - Caravans;
- > Stable electric current without oscillations;
- > Silent and more efficient in terms of consumption;
- > Lightweight and easy to transport;
- > Easy and smooth / fast electric start.

### Package Contents

- > Inverter generator VIGI3000
- > Oil funnel
- > DC output cable
- > 16A schuko plug
- > Set of wrenches
- > Instruction manual.